

PHILCO RADIO MODELS 50-522, 50-522-I and 50-524

SPECIFICATIONS

CABINET

Model 50-522Molded plastic, mottled mahogany

Model 50-522-IMolded plastic, ivory

Model 50-524Wood, mahogany finish

CIRCUIT.....5-tube superheterodyne

FREQUENCY RANGE.....540—1620 kc.

AUDIO OUTPUT.....1.2 watts


OPERATING VOLTAGE.....105—125 volts, a.c. or d.c.

POWER CONSUMPTION.....30 watts


AERIALHigh-impedance loop; connector for external aerial

INTERMEDIATE FREQUENCY.....455 kc.

PHILCO TUBES (5).....7A8, 12BA6, 14B6, 50L6GT, 35Z5GT



MODEL 50-522
MODEL 50-522-I



MODEL 50-524

TP-7807

TP-7803

Circuit Description

Philco Models 50-522, 50-522-I, and 50-524 are 5-tube, table-model superheterodyne radios, providing reception in the standard broadcast band. These three models are identical except for the cabinets and certain cabinet parts, as indicated in the Replacement Parts List.

The high-impedance loop aerial normally provides adequate signal pickup. An external aerial may be connected, if desired, by attaching the lead to lug No. 4 (shown in figure 6) on the rear of the chassis. Do not use a ground.

The converter employs a 7A8 tube. Variable-condenser tuning is used; the rotor plates of the oscillator section are specially shaped to obtain tracking, thus eliminating the necessity for a series padding condenser.

The 7A8 is transformer-coupled to the 12BA6 i-f amplifier, which is, in turn transformer-coupled to the diodes of the 14B6 detector-first audio amplifier. A-v-c voltage is applied to the control grids of the i-f and converter tubes.

The triode section of the 14B6 is the first audio amplifier, and is resistance-coupled to the 50L6GT output tube, which works into a permanent-magnet speaker.

D-c operating voltages are obtained from a 35Z5GT half-wave rectifier, the output of which is filtered by a two-section resistance-capacitance filter.

Resistor R100, 150,000 ohms (in Section 1), prevents hum which might otherwise occur under conditions of high humidity.

Philco TROUBLE-SHOOTING Procedure

For rapid trouble shooting, the radio circuit is divided into four sections, with test points specified for each section; these sections and test points are indicated in the schematic

diagram. The trouble-shooting procedure given for each section includes a simplified test chart and a bottom view of the chassis showing the locations of the test points and the components of that section.

In each chart, the first step is a master check for determining whether trouble exists in that section without going through the entire test procedure.

Failure to obtain the "NORMAL INDICATION" in any given step indicates trouble within the circuit under test.

After isolating the trouble to a single stage, the defect is located by: first, testing the tube; second, measuring tube electrode voltages; third, measuring circuit resistances; fourth, substituting condensers. The trouble revealed should be corrected before testing further.

Preliminary Checks

To avoid possible damage to the radio, the following preliminary checks should be made before it is turned on:

1. Inspect both the top and bottom of the chassis. Make sure that all tubes are secure in the proper sockets, and look for any broken or shorted connections, burned resistors, or other obvious indications of trouble.

2. Measure the resistance between B+ (test point C) and B- (test point B). See figure 1. When the ohmmeter test leads are connected in the proper polarity, the highest resistance reading will be obtained. If the reading is lower than 1500 ohms, check condensers C101A, C101B, C101C, and C203 for leakage or shorts. The resistance value given is much lower than normal, and is not intended as a quality check of these condensers; the value given is the lowest at which the rectifier will operate safely while the voltage checks of Section 1 (power supply) are performed.

Section 3—I-F, Detector, and A-V-C Circuits

TROUBLE SHOOTING

For the tests in this section, use an r-f signal generator, with modulated output, set at 495 kc. Connect the generator ground lead to B—, test point B; connect the output lead through a .1- μ f. condenser to the test points indicated in the chart.

Set the volume control to maximum, and turn the tuning control until the tuning condenser is fully meshed.

If the "NORMAL INDICATION" is obtained in step 1, proceed with the tests for Section 4 (r-f and converter circuits); if not, isolate and correct the trouble in this section.

To provide a complete i-f-amplifier check, test point A for this section is placed at the grid of the mixer in Section 4; therefore, the effectiveness of step 1 as a master check is dependent upon the condition of certain parts in the mixer circuit. These parts are listed below under "POSSIBLE CAUSE OF ABNORMAL INDICATION."




Figure 3. Bottom View, Showing Section 3 Test Points

STEP	TEST POINT	NORMAL INDICATION	POSSIBLE CAUSE OF ABNORMAL INDICATION
1	A	Loud, clear speaker output with weak signal input.	Trouble in this section. Isolate by the following tests.
2	C	Loud, clear output with moderate input.	Defective: 12BA6, 14B6, (diode section). Misaligned: Z301. Open: R300, C301A, C301B, L301A, L301B, R302, R303. Shorted: C302, C300B, C301A, C301B, C301C.
3	A	Same as step 1.	Defective: 7A8*. Misaligned: Z300. Open: L300A, L300B, R301, C300A, C300B. Shorted: C300A, C400, C400A.

* This part, located in another section, may cause abnormal indication in this section.

Section 4—R-F and Converter Circuits

TROUBLE SHOOTING

For the tests in this section, with the exception of the oscillator test, use an r-f signal generator with modulated output. Connect the generator ground lead to B—, test point B; connect the output lead through a .1- μ f. condenser to the test points indicated in the chart.

Set the volume control to maximum. Set the tuning control and the signal-generator frequency as indicated in the chart.

If the "NORMAL INDICATION" is not obtained in step 1, isolate and correct the trouble in this section. If the trouble is not revealed by the tests for this section, check the alignment.




Figure 4. Bottom View, Showing Section 4 Test Points

STEP	TEST POINT	SIG. GEN. FREQ.	RADIO TUNING	NORMAL INDICATION	POSSIBLE CAUSE OF ABNORMAL INDICATION
1	A	1000 kc.	1000 kc.	Loud, clear speaker output with weak signal input.	Trouble in this section. Isolate by the following tests.
2	C Osc. test; see note below.		Tune through range.	Negative 4.5 to 7.5 volts.	Defective: 7A8. Open: C401, T400, R400. Shorted: T400, C401, C400, C400B, C402.
3	A	1000 kc.	1000 kc.	Same as step 1.	Defective: 7A8. Open: LA400. Shorted: C400, C400A, LA400.

OSCILLATOR TEST: Connect the positive lead of a high-resistance voltmeter to B—, test point B; connect the prod end of the negative lead through a 100,000-ohm isolating resistor to the 7A8 oscillator grid (pin 4), test point D. Use a suitable meter range, such as 0–10 volts. Proper operation of the oscillator is indicated by negative voltage of approximately the value given in the chart (measured with 20,000-ohms-per-volt meter), throughout the tuning range.






Figure 5. Philco Radio Models 50-522, 50-522-I, and 50-524, Sectionalized Schematic Diagram, Showing Test Points

ALIGNMENT PROCEDURE

CONTROLS: Turn on the radio, and set the volume control to maximum.

DIAL POINTER: Turn the tuning condenser to the full-mesh position. Set the dial pointer to the index mark, located to the left of "55."

OUTPUT METER: Connect across the voice-coil terminals.

SIGNAL GENERATOR: Connect as indicated in the chart.

OUTPUT LEVEL: During the alignment, adjust the signal-generator output to hold the output-meter indication below 1.25 volts.

STEP	SIGNAL GENERATOR		RADIO		ADJUST
	CONNECTION TO RADIO	DIAL SETTING	DIAL SETTING	SPECIAL INSTRUCTIONS	
1	Ground lead to B—; output lead through .1- μ f. condenser to pin 6 of 7A8 tube.	455 kc.	540 kc. (gang fully meshed).	Adjust tuning cores, in order given, for maximum output.	TC301B—2nd i-f sec. TC301A—2nd i-f pri. TC300B—1st i-f sec. TC300A—1st i-f-pri.
2	Radiating loop; see note below.	1600 kc.	1600 kc.	Adjust for maximum.	C400B—osc.
3	Same as step 2.	1500 kc.	1500 kc.	Adjust for maximum.	C400A—aerial

NOTE: TC300A AND TC301A ARE LOCATED ON UNDERSIDE OF CHASSIS




Figure 6. Top View, Showing Trimmer Locations

RADIATING LOOP: make up a 6–8 turn, 6-inch-diameter loop from insulated wire; connect to signal-generator leads and place near radio loop aerial.

SYMBOLIZATION

The components in the radio circuit are symbolized according to the types of parts and the sections of the radio in which the parts are located. The prefix letter of the symbol designates the type of part, as follows:

- | | |
|-----------------|-----------------------|
| C—condenser | R—resistor |
| I—pilot lamp | S—switch |
| L—choke or coil | T—transformer |
| LA—loop aerial | W—line cord |
| LS—loud-speaker | Z—electrical assembly |

The number of the symbol designates the section in which the part is located, as follows:
 100-series components are in Section 1—the power supply.
 200-series components are in Section 2—the audio circuits.
 300-series components are in Section 3—the i-f amplifier, detector, and a-v-c circuits.
 400-series components are in Section 4—the r-f and converter circuits.




Figure 7. Drive-Cord-Installation Details

REPLACEMENT PARTS LIST

NOTE: Part numbers identified by an asterisk (*) are general replacement items. These numbers may not be identical with those on factory parts; also, the electrical values of some replacement items may differ from the values indicated in the schematic diagram and parts list. The values substituted in any case are so chosen that the operation of the radio will be either unchanged or improved. When ordering replacements, use only the "Service Part No."

SECTION 1

POWER SUPPLY

Reference Symbol	Description	Service Part No.
C100	Condenser, line filter, .04 μ f.	45-3500-2*
C101	Condenser, electrolytic, 3-section filter	30-2573
C101A	Condenser, filter, 30 μ f., 150 v.	Part of C101
C101B	Condenser, filter, 25 μ f., 150 v.	Part of C101
C101C	Condenser, filter, 20 μ f., 150 v.	Part of C101
R100	Resistor, leakage, 150,000 ohms	66-4158340*
R101	Resistor, filter, 220 ohms, 1 watt	66-1224340*
R102	Resistor, filter, 1200 ohms	66-2128340*
S100	Switch, off-on	Part of R200
W100	Line cord and plug	L-2183*

SECTION 2

AUDIO CIRCUITS

C200	Condenser, d-c blocking, .01 μ f.	61-0120*
C201	Condenser, d-c blocking, .01 μ f.	61-0120*
C202	Condenser, by-pass, 220 μ f.	62-122001001*
C203	Condenser, tone compensation, .02 μ f.	61-0108*
LS200	Speaker, p-m, 4"	36-1627-5
R200	Volume control (with off-on switch), 500,000 ohms	33-5566-4
R201	Resistor, grid return, 3.3 megohms	66-5338340*
R202	Resistor, plate load, 470,000 ohms	66-4478340*
R203	Resistor, grid return, 470,000 ohms	66-4478340*
R204	Resistor, cathode bias, 130 ohms, 1 watt	
T200	Transformer, output	32-8384

SECTION 3

I-F, DET. AND A-V-C CIRCUITS

C300A	Condenser, fixed trimmer	Part of Z300
C300B	Condenser, fixed trimmer	Part of Z300
C301A	Condenser, fixed trimmer	Part of Z301
C301B	Condenser, fixed trimmer	Part of Z301
C301C	Condenser, i-f filter	Part of Z301
C301D	Condenser, i-f filter	Part of Z301
C302	Condenser, screen by-pass, .003 μ f.	61-0109*
C303	Condenser	
C304	Condenser, a-v-c by-pass, .05 μ f.	61-0122*
L300A	Coil, 1st i-f primary	Part of Z300
L300B	Coil, 1st i-f secondary	Part of Z300
L301A	Coil, 2nd i-f primary	Part of Z301
L301B	Coil, 2nd i-f secondary	Part of Z301
R300	Resistor, screen dropping, 39,000 ohms	66-3398340*
R301	Resistor, grid return, 330,000 ohms	66-4338340*
R302	Resistor, i-f filter, 47,000 ohms	66-3478340*
R303	Resistor, diode load, 2.2 megohms	66-5228340*
TC300A	Tuning core, 1st i-f primary	Part of Z300

SECTION 3 (Cont.)

Reference Symbol	Description	Service Part No.
TC300B	Tuning core, 1st i-f secondary	Part of Z300
TC301A	Tuning core, 2nd i-f primary	Part of Z301
TC301B	Tuning core, 2nd i-f secondary	Part of Z301
Z300	Transformer, 1st i-f	
Z301	Transformer, 2nd i-f	32-4240-A

SECTION 4

R-F AND CONVERTER

C400	Condenser, tuning gang, 2-section	31-2727-2
C400A	Condenser, trimmer, aerial	Part of C400
C400B	Condenser, trimmer, oscillator	Part of C400
C401	Condenser, d-c blocking, 47 μ f.	60-00515307*
C402	Condenser, fixed trimmer, 10 μ f.	30-1224-26*
LA400	Loop aerial	
	Model 50-522, 50-522-I	32-4052-31
	Model 50-524	32-4052-34
R400	Resistor, grid return, 100,000 ohms	66-4108340
T400	Transformer, oscillator	32-4263

MISCELLANEOUS

Description	Service Part No.
Cabinet	
Model 50-522	10747
Model 50-522-I	10747-1
Model 50-524	10754
Back	
Model 50-522, 50-522-I	54-7767
Model 50-524	54-7810
Fastener, cabinet back (4), 50-522, 50-522-I	W2235-2FA9
Dial scale, Model 50-524	
Scale strap (2)	56-7021-FA3
Knob	
Model 50-522	54-4674
Model 50-522-I	54-4674-1
Model 50-524	54-4527-3
Dial-backplate assembly	76-4570
Drive cord (25-ft. spool)	45-8750*
Spring, drive cord	56-2617
Drive-shaft-and-pulley assembly	76-3671-2
Pointer	56-5630-11
Spring, pointer	56-3167
Rubber mounts, gang mounting (3)	27-4771-1
Socket, Loktal (2)	27-6138*
Socket, miniature (1)	27-6203
Socket, octal (2)	27-6174*

CORRECTIONS TO PARTS LIST

Reference Symbol	Description	Service Part No.
R204	Resistor, cathode bias, 130 ohms, 1 watt.	66-1133340*
C303	Condenser and choke assembly, .003 μ f.	38-9851-12
Z300	Transformer, 1st i-f	32-4160-6A
	Dial scale (50-524)	54-5060-1

PRODUCTION CHANGES

ALL MODELS

Code 121, Run 2

To increase sensitivity, the following changes were made:

Grid return resistor R301 was changed to 470,000 ohms, Part No. 66-4478340*.

The condenser-and-choke assembly, C303, was replaced by a .1- μ f. condenser, Part No. 61-0113*.

The 10- μ f. fixed trimmer condenser, C402, Part No. 30-1224-26*, was added. (This condenser was not used in Run 1.)

Code 121, Run 3

To improve power sensitivity, a 1-megohm resistor, Part No. 66-5108340*, was added, as an a-v-c voltage divider, from pin 5 of the 14B6 to B-.

MODEL 50-522

Code 121, Run 4

To improve tone, the following changes were made: The tone compensating condenser, C203, was changed to Part No. 61-0122*.

A 2200-ohm resistor, Part No. 66-2228340*, was added, between condenser C203 and pin 3 of the 50L6GT.

Code 122, Run 1

The 35Z5GT tube was replaced by a 35Y4, and the 50L6GT was replaced by a 50C5, with the necessary wiring changes.