

SUPPLEMENT

WESTINGHOUSE MODELS H-104A, H-105A, H-107A, H-108A, H-154

These models are the same as Models H-104, H-105, H-107, H-108 with the exceptions listed below. Also note the change in the tone control circuit shown on schematic diagram on reverse side of this page.

TUBES (SYLVANIA or Equivalent)

ITEM No.	USE	REPLACEMENT DATA		RMA BASE TYPE	INSTALLATION NOTES
		WESTINGHOUSE PART No.	STANDARD REPLACEMENT		
4	Det.-AVC-AF	6AT6	6AT6	7BT	

CAPACITORS

Capacity values given in the rating column are in mfd. for Electrolytic and Paper Capacitors, and in mmfd. for Mica and Ceramic Capacitors.

ITEM No.	RATING		REPLACEMENT DATA					IDENTIFICATION CODES AND INSTALLATION NOTES	
	CAP.	VOLT	WESTINGHOUSE PART No.	CORNELL-DUBILIER PART No.	MALLORY PART No.	SOLAR PART No.	SPRAGUE PART No.		AEROVOX PART No.
9	NOT USED								
14	NOT USED								
15	NOT USED								
73	.002	600	RCP10W6202A	DT6D2	TP405	S-6-002	TC-22	684-002	Audio Coupling

RESISTORS

ITEM No.	RATING		REPLACEMENT DATA		IDENTIFICATION CODES
	RESISTANCE	WATTS	WESTINGHOUSE PART No.	IRC PART No.	
41	NOT USED				
42	NOT USED				
43	470K Ω	$\frac{1}{2}$	RC10AE474M	BTS-470K	Y1.-V1.-Y1. AF Plate Load
44	NOT USED				
74	10 Meg.	$\frac{1}{2}$	RC10AE106M	BTS-10 Meg	Br.-Blk.-Blue AF Grid

ADD THE FOLLOWING PART NUMBERS

Loop Antenna Coil.....	V-3283-1	Osc. Cathode Coil.....	V-3313
BC Antenna Coil.....	V-3238	Input IF Coil.....	V-3218
SW Antenna Coil.....	V-3224	Output IF Coil.....	V-3249
BC RF Coil.....	V-3245	Band - Phono Switch.....	V-3289
BC Osc. Coil		Pushbutton Assembly.....	V-3317
SW Osc. Coil	V-3243	Tuning Capacitor.....	V-3233

VOLTAGE READINGS

Item	Tube	Pin 1	Pin 2	Pin 3	Pin 4	Pin 5	Pin 6	Pin 7
4	6AT6	±5V,DC	OV,✓	OV,✓	6.2V,AC	±5V,DC	OV,✓	70V,DC

RESISTANCE READINGS

Item	Tube	Pin 1	Pin 2	Pin 3	Pin 4	Pin 5	Pin 6	Pin 7
4	6AT6	10MEG Ω	0 Ω	0 Ω	0 Ω	500K Ω	0 Ω	700K Ω

HOWARD W. SAMS & CO., INC. • 2924 East Washington Street • Indianapolis 6, Indiana

"The listing of any available replacement part herein does not constitute in any case a recommendation, warranty or guaranty by Howard W. Sams & Co., Inc., as to the quality and suitability of such replacement part. The numbers of these parts have been compiled from information furnished to Howard W. Sams & Co., Inc., by the manufacturers of the particular type of replacement part listed."
"Reproduction or use, without express permission, of editorial or pictorial con-

tent, in any manner, is prohibited. No patent liability is assumed with respect to the use of the information contained herein. Copyright 1947 by Howard W. Sams & Co., Inc., Indianapolis, Indiana, U. S. A. Copyright under International Copyright Union. All rights reserved under Inter-American Copyright Union (1910) by Howard W. Sams & Co., Inc." Printed in U. S. of America

SET #21 DATE 7/47 FOLDER #4711-36